RUNLUX | Linear High Bay Installation Guide

PRODUCT DESCRIPTION:

Runlux LED Linear High Bay Fixture with exceptional 130+ LPW output, for commercial or industrial application. The low profile and durable design allow for mounting heights ranging from 3 to 12 meters (10 to 40 feet).

Model Selection

Rated Power	Model No.	Efficacy	CCT	Description
95W	R2-2LHB95WD-XXK	130LM/W	4000K 5000K	120-277V, L647.6*W373.4*H53mm, CRI80, Dimming (0-10V)
105W	R2-2LHB105WD-XXK			120-277V, L647.6*W373.4*H53mm, CRI80, Dimming (0-10V)
110W	R2-2LHB110WDH-XXK			120-277V, L647.6*W373.4*H53mm, CRI80, Dimming (0-10V)
130W	R2-2LHB130WD-XXK			120-277V, L647.6*W460*H53mm, CRI80, Dimming (0-10V)
135W	R2-2LHB130WD-XXK			120-277V, L647.6*W460*H53mm, CRI80, Dimming (0-10V)
150W	R2-2LHB150WD-XXK			120-277V, L647.6*W460*H53mm, CRI80, Dimming (0-10V)
162W	R2-2LHB162WDH-XXK			120-277V, L647.6*W460*H53mm, CRI80, Dimming (0-10V)
190W	R2-2LHB190WD-XXK			120-277V, L647.6*W460*H53mm, CRI80, Dimming (0-10V)
223W	R2-2LHB223WDH-XXK			120-277V, L647.6*W460*H53mm, CRI80, Dimming (0-10V)
150W	R2-4LHB150WD-XXK			120-277V, L1200*W373.4*H53mm, CRI80, Dimming (0-10V)
190W	R2-4LHB190WD-XXK			120-277V, L1200*W373.4*H53mm, CRI80, Dimming (0-10V)
210W	R2-4LHB210WD-XXK			120-277V, L1200*W373.4*H53mm, CRI80, Dimming (0-10V)
223W	R2-4LHB223WD-XXK			120-277V, L1200*W373.4*H53mm, CRI80, Dimming (0-10V)
300W	R2-4LHB300WD-XXK			120-277V, L1200*W460*H53mm, CRI80, Dimming (0-10V)
321W	R2-4LHB321WD-XXK			120-277V, L1200*W460*H53mm, CRI80, Dimming (0-10V)
420W	R2-4LHB420WD-XXK			120-277V, L1200*W460*H53mm, CRI80, Dimming (0-10V)

IMPORTANT SAFETY INFORMATION:

▶Make sure that the supply voltage corresponds to the rated product voltage.

▶ The product must be installed by a qualified electrician in accordance with the National Electrical Code and corresponding local codes. If the product is damaged, do not use it.

▶ All wiring connections should be capped with UL approved wire connectors.

INSTALLATION :

1. Chain mount .
2. Pendant mount – (customer supplied option)





ASSEMBLING FIXTURE:

1. Remove the covers from the both sides of the fixture.
2. Pass the power cord into the driver and connect it to driver wires: white, black and green.
3. Pass dimmer wires into the hole and connect them with violet and grey wires.
4. Close the cover

RUNLUX